

System Information

Last Modified on 11.26.24

The **System Information** tool displays a variety of system information and allows several right click actions.

This action can be run on single and multi-selected devices, or with a similar tool designed for device collections.

To run the tool:

1. In your Configuration Manager console, right-click on a device.

2. Click Right Click Tools > Console Tools > System Information.

System Information Tabs

The System Information tool displays data in the following categories: Operating System, Hardware, Applications, Windows Updates, Services, Drivers, User Profiles, User Sessions, Local Group Members, Batteries.

NOTE: When running System Information against multiple devices or a collection, each of the devices will be represented in the results and can be multi-selected.

Operating System

The **Operating System** tab displays details including OS Version, Install Date, Domain, Console User, Last Boot Time and computer information including Manufacturer, Model, Serial Number, BIOS Version and BIOS Release Date.

>_	Operating Systems											Refresh
	Hardware	\odot	 Operating System OS Version 			ion OS Build				Devices		
	Applications	\odot	Microsoft Windows 10 Enterprise 10.0.17134				1803			1		
-	- pp		Name RECAST_DEMO_2 RECASTSOFT	WARELOCAL	IP Address	Domain RECASTSOFTWARE LO	Console User	Pending Restart	OS Install Da	ate 5:57:25 PM	Last Boot Time	
ΰ	Windows Updates		RECAST-DEMO-ERECASTSOT	ANELOCAL	152.100.100.10	NECKS15011WARELED		Tube	10/15/2010 0	.51.25 P W	3/23/2020 11.11.00 AM	
0	Services											
	Drivers											
8	User Profiles											
ii)	Local Group Members											
	Batteries											
RECA	ST SOFTWARE											0.5

Hardware

0 Errors 🔿

The **Hardware** tab displays details including the Name, Serial Number, MAC Address, BIOS version and BIOS Release Date.

>_	Operating Systems									Refresh
	Hardware	\odot	Manufacturer	Model			Devices			
	Applications	\odot	Microsoft Corporation	Virtual Machine			1			
S	Windows Updates		Name RECAST-DEMO-2.RE	ECASTSOFTWARE.LOCAL	Serial Number 0000-0008-1199-8496-2748-5001-38	Number MAC Address 008-1199-8496-2748-5001-38 8E:5C:20:52:41:53 / A0:8B:20:52:41:53 / AC:8E:20:52:41:53		BIOS Version 090007	BIOS Release Date 6/1/2017 7:00:00 P	M
0	Services									
	Drivers									
2	User Profiles									
ċ	Local Group Members									
	Batteries									
RECA	AST SOFTWARE									0 Errors 🔿

Applications

The **Applications** tab displays details including application Name, Publisher, Architecture, Version number, Uninstall String, and Devices.

NOTE: Uninstall strings are pulled via the Remote Registry service and added during Right Click Tools installation.

Clicking an application select box reveals the option to uninstall the application.

 >_	Operating Systems							Refresh Uninsta	ill
	Hardware	\odot	Name	Publisher	Architecture	Version	Uninstall String	Devices	
		\odot	Windows Firewall Configuration Provider	Microsoft Corporation	x64	1.2.3412.0	msiexec /x {109A5A16-E09E-	1	^
별	Applications	\odot	7-Zip 19.00 (x64 edition)	Igor Pavlov	х64	19.00.00.0	msiexec /x {23170F69-40C1-	1	
Ð	Windows Updates	\odot	Microsoft Visual C++ 2019 X64 Minimum Runtime - 14.28.29914	Microsoft Corporation	x64	14.28.29914	msiexec /x {455DF12C-7D43	1	
-	Senices	\odot	Recast Privilege Manager (64-bit)	Recast Software, Inc.	x64	3.1.5021.46	msiexec /x {536D5657-AC54	1	
	Services	\odot	Microsoft Visual C++ 2013 x64 Additional Runtime - 12.0.40660	Microsoft Corporation	x64	12.0.40660	msiexec /x {5740BD44-B58D	1	
	Drivers	\odot	Microsoft Visual C++ 2019 X64 Additional Runtime - 14.28.29914	Microsoft Corporation	x64	14.28.29914	msiexec /x {5A23DBE2-A05C	1	
	User Profiles	\odot	Microsoft Policy Platform	Microsoft Corporation	x64	68.1.1010.0	msiexec /x {6549B04F-E826-	1	
		\odot	Firefox x64	Mozilla	x64	107.0.1	msiexec /x {6F027831-A3D2	1	
	User Sessions	\odot	Configuration Manager Client	Microsoft Corporation	х64	5.00.9078.1000	msiexec /x {918DD4C3-F020	1	
i	Local Group Members	\odot	Google Chrome (64-bit)	Google LLC	x64	108.0.5359.95	msiexec /x {9D24A55A-BF91	1	
	Pethoday	\odot	Adobe Acrobat Reader DC (64-bit)	Adobe	x64	22.003.20282	msiexec /x {AC76BA86-1033	1	-
	Batteries		MDOP MBAM	Microsoft Corporation	x64	2.5.1152.0	msiexec /x {AEC5BCA3-A2C5	1	
		â	Microcoft Vicual C++ 2013 v64 Minimum Runtime - 12.0.40660	Microsoft Corporation	v64	12.0.40660	mriever /v /CR0836EC_R072	1	\sim
RECA	IST SOFTWARE							0 Errors (\odot

Windows Updates

The **Windows Updates** tab shows information such as the corresponding KB article and description, as well as when the update was installed and who installed it.

Clicking on an KB Article name opens the support.microsoft.com page about that particular knowledge base article.

 >_	Operating Systems			Refresh
	Hardware	S KB Article	Description	Devices
	Applications		Update	1
별			Update	1
S	Windows Updates		Update	1
ð	Services	⊙ □ <u>KB4465659</u>	Security Update	1
	Scivices		Security Update	1
	Drivers	✓ ☐ KB4494175	Update	1
2	User Profiles	⊙ □ <u>KB4498947</u>	Security Update	1
	Local Group Members		Security Update	1
ă		📀 🗌 КВ4509091	Security Update	1
	Batteries	📀 🗌 КВ4520724	Security Update	1
		📀 🗌 КВ4537764	Security Update	1
RECA	\$T SOFTWARE			0 Errors 🔿

Services

The **Services** tab displays the Status Startup Type and description of each service for a device.

Clicking on a service opens options to start, stop, or restart the service and specify the startup type for the service.

>_ Operating Systems		Refresh Start Service Y Start Automatic Y
Hardware	💿 🗆 Display Name Name	Devices
Applications	Microsoft Monitoring Agent Audit Forwarding AdtAgent Sends events to a collector for storage in a SQL database.	1
O Windows Updates	Name Status Statup Type RECAST-DEMO-2.RECASTSOFTWARE.LOCAL Stopped Disabled	
Services	⊘ □ AllJoyn Router Service AJRouter	1
Drivers	Application Layer Gateway Service ALG	1
•		1
User Profiles	Application Information Appinfo	1
Local Group Members	Application Management AppMgmt	1
Ratteries		1
batteries	Microsoft App-V Client AppVClient	1
		1
		0 Errors 🐼

0 Errors 🔿

Drivers

The Drivers tab shows information about the device's drivers such as Device Name, Device Class, Driver Date, Driver Version, Signed Status and Device ID.

>_ Operating Systems							Refresh
Hardware	Device Name	Device Class	Driver Date	Driver Version	Is Signed	Device ID	Devices
	Generic software devi	e SOFTWAREDEVICE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\SCDEVICEENUMBU	S\ 1
Applications	Generic software devi	e SOFTWAREDEVICE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\SCDEVICEENUM\2_	_W 1
G Windows Updates	Generic software devi	e SOFTWAREDEVICE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\SCDEVICEENUMBU	S\ 1
-	 Local Print Queue 	PRINTQUEUE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\PRINTENUM\{083C	A' 1
Services	✓ Local Print Queue	PRINTQUEUE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\PRINTENUM\{15A5	E3 1
Drivers	 Local Print Queue 	PRINTQUEUE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\PRINTENUM\{83F7	4B 1
	 Local Print Queue 	PRINTQUEUE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\PRINTENUM\{244A	.8E 1
User Profiles	 Local Print Queue 	PRINTQUEUE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\PRINTENUM\{3EFF8	88 1
Local Group Memberr	 Local Print Queue 	PRINTQUEUE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\PRINTENUM\{7F21	1C 1
	 Local Print Queue 	PRINTQUEUE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\PRINTENUM\{4900	75 1
Batteries	 Local Print Queue 	PRINTQUEUE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\PRINTENUM\{9E65	0C 1
	 Local Print Queue 	PRINTQUEUE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\PRINTENUM\{1CC1	Al 1
	 Local Print Queue 	PRINTQUEUE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\PRINTENUM\{5644	AE 1
	 Local Print Queue 	PRINTQUEUE	6/21/2006 12:00:00 AM	10.0.14393.0	True	SWD\PRINTENUM\{E6A4	451 🗸

User Profiles

The **User Profiles** tab shows information on users that have signed onto the device. Details include Last Used, In WMI, In Registry, Profile Path Exists and SID.

Clicking on a profile reveals the option to delete the selected profile and its associated registry key. **NOTE**: Clicking **Delete** removes the user profile immediately, without requiring confirmation.

>_	Operating Systems					Refresh	Delete	
	Hardware	\odot	Username	SID	Devices			
	A 17 17	\odot	.NET v4.5 Classic	S-1-5-82-3876422241-1344743610-1729199087-774402673-2621913236	1			^
딸	Applications	\odot	Recast Management Server	S-1-5-82-3437154273-3411812188-591949707-1062958709-582427915	1			
S	Windows Updates	\odot	.NET v4.5	S-1-5-82-271721585-897601226-2024613209-625570482-296978595	1			
a	Services	\odot	MSSQL\$SQLEXPRESS	S-1-5-80-3880006512-4290199581-1648723128-3569869737-3631323133	1			
	Services	\odot	SQLTELEMETRY\$SQLEXPRES	S S-1-5-80-1985561900-798682989-2213159822-1904180398-3434236965	1			
	Drivers	\odot	Administrator	S-1-5-21-2721313014-1803048728-2293401446-500	1			
2	User Profiles	\odot	gMSARecast\$	S-1-5-21-2713758348-1654692784-2107250698-1199	1			
-		\odot	bryand-adm	S-1-5-21-2713758348-1654692784-2107250698-1180	1			
í	Local Group Members	\odot	test&#.user</th><th>S-1-5-21-2713758348-1654692784-2107250698-1167</th><th>1</th><th></th><th></th><th></th></tr><tr><th></th><th>Batteries</th><th>\odot</th><th>roba-adm</th><th>S-1-5-21-2713758348-1654692784-2107250698-1165</th><th>1</th><th></th><th></th><th></th></tr><tr><th></th><th></th><th>\odot</th><th>rctsvc</th><th>S-1-5-21-2713758348-1654692784-2107250698-1141</th><th>1</th><th></th><th></th><th></th></tr><tr><th></th><th></th><th>\odot</th><th>chrism-adm</th><th>S-1-5-21-2713758348-1654692784-2107250698-1106</th><th>1</th><th></th><th></th><th></th></tr><tr><th>~</th><th></th><th>-</th><th>markq_adm</th><th>S_1_5_21_2713758348_1654602784_2107250608_1105</th><th>1</th><th></th><th></th><th>\sim</th></tr><tr><th>RECA</th><th>5T SOFTWARE</th><th></th><th></th><th></th><th></th><th></th><th>0 Errors (</th><th>\odot</th></tr></tbody></table>					

User Sessions

The **User Sessions** tab shows details about the user sessions on the device, including the connection status and the duration.

Clicking on a user session reveals the option to log off the selected user session.

>_ Operating Systems	Refresh Logoff
Hardware	🕟 🗆 Username Domain Devices
Applications	martym DEV 1 Num Created for Learned One Influence Discussed of Section Neuro
O Windows Updates	Name Status Connected instruction Disconnected session name KioskTest.dev.recastsoftware.com Disconnected 19:56 18:32 18:32
Services	
Drivers	
User Profiles	
User Sessions	
Local Group Members	
Batteries	
RECAST SOFTWARE	0 Errors (

Local Group Members

The Local Group Members tab shows the Group Name, Member Domain and Member Name for each Local Group.

Selecting a Group or Group Member reveals the option to delete the group or group member.

	Occurring Systems		Refrech	Remove		
>_	Operating Systems		Nellesti	Nemove		
	Hardware	Group Name Members				
몓	Applications	Image: Construction Administrators Image: Construction 1				
Ð	Windows Updates	C Cuess I Cues				
0	Services	⊙ □ Guest 1				
	Drivers	Computer Name Member Domain Member Name Group Name RECAST-DEMO-2.RECASTSOFTWARE.LOCAL RECAST-DEMO-2 Guest Guests				
2	User Profiles					
i	Local Group Members					
	Batteries	☑ Users 3				
		ConfigMgr Remote Control Users 1				
RECA	ST SOFTWARE			0 Errors 🔿		

Batteries

The **Batteries** tab shows battery details such as Status, Type, Condition and Estimated Charge Remaining.

 >_	Operating Systems								
	Hardware	\odot	Name	Туре			Devices		
œ	Applications	\odot	5018455836SMPM1010958 L	Lithium-ion	-		1		
ือ	Windows Updates		Name SurfaceBook.corp.viamonst	Availability tra.com Unknown	itus e system has access to AC so no battery is being discharg	ed. However, the battery is not n	eccessarily charging.	Estimated Charge Remaining 100	OK
ă	Services	\odot	0030047834DYNM1005046 L	Lithium-ion			1		
	Driver		Name SurfaceBook.corp.viamonst	Availability tra.com Unknown	tus e system has access to AC so no battery is being discharg	ed. However, the battery is not n	eccessarily charging.	Estimated Charge Remaining 100	Condition OK
	Drivers								
ĕ	User Profiles								
ä	Local Group Members								
	Batteries								

Recast Permissions

Installed Software plugin	ListSoftware		
	UninstallSoftware		
Services plugin	StartService		
	ChangeStartModeManual		
	RestartService		
	ChangeStartModeDisabled		
	ChangeStartModeAutomaticDelayedStart		
	StopService		
	ListServices		
System Information plugin	UpdateLocalGroupMembership		
	DeleteProfile		

Microsoft Permissions

- Requires local administrator permissions on the remote devices.
- If using a Recast Management Server with a proxy, the service account needs local administrator permissions on the remote devices.
- This tool requires Remote WMI and Remote Registry access.

Copyright © 2024 Recast Software Inc. All rights reserved.